

MYT-7.0 Lite 2G



Presentation of the product

Galileosky 7 is a range of terminals in a compact plastic case equipped with buil-in aerials and additional fasteners. Apart from a broad range of options the terminals support Easy Logic technology of independent programming.



Connection of additional devices

- CAN
- CAN-bus protocol support J1939 (FMS, Scanner, User_29bit, User_11bit)
- CAN-bus protocol support J1979 (Scanner, User_29bit, User_11bit)
- RS485
- Eurosens Delta
- UHF RFID Reader
- Tachograph SHTRIH-TaxoRUS
- Tachograph Mercury TA-001
- SENS
- RFID reader Matrix 5
- Digital fuel level sensors
- Galileosky photo camera
- Dosimeter DBG-S11D
- DAI
- Analog-frequency fuel level sensors
- Pulse flowmeters
- Passenger traffic flow sensors
- Analog emergency button



Specifications

General Assistance Consultation Bell	Galileosky 7.0 Lite
GLONASS/GPS unit	Yes TURQUIS
Iridium satellite unit	No Alhenes
Bluetooth	No r a n 6 Járusalem 1 1RAK
GSM-modem	GSM 850/900/1800/1900
Types of aerials (GLONASS/GPS, GSM)	Internal Assource Media
Data transmission channel	GPRS/SMS Wadt Halls La Meeque Le
Cold start	25 Port Sudan
Hot start	HID Omdurmane Rharloum Asmara YKMEN, VES
Coordinates determination accuracy	5 m S O U D A N Addis Abelia
Support of 2G	Yes
Support of 3G	No water
Support of Wi-Fi	No Kaangani Kenya
Internal memory capacity (Mb)	16 IR E Victoria
Maximum number of points in the internal memory	450000 Tabora Mombasa TANZANIE Tanganyha Spar es Salaam
External memory capacity (Gb)	A Lubumbashi S I Lac COMORES
Number of slots for SIM-cards	2 Mayatte (fr.)
Availability of an input for micro-SD card	No ZIMBABWE Operate State Stat
Opportunity to install a SIM-chip	Yesotswan Bulandayo
Interface of connection with PC	USB 2.0
Digital interfaces	CAN, RS485, USB
ADC resolution	16
Inputs & Outputs	Port Elizabeth
Number of analog inputs	6



Number of transistor outputs	4
Number of RS232 digital inputs	-
Number of RS485 digital inputs	rid Ner Note PortoAlexand
Availability of 1-Wire digital input	No Sistanbul Ankara Athli C. Fria
Availability of Jack 3,5 input for speaker	No Atheres Chypre Symus
Availability of Jack 3,5 input for loud speaker	NO Alexandrie I Amman Swake
Availability of Jack 2,5 input for loud speaker	No EGYP E Assource Medine
Functions	Wast Halla La Meeque Le
Opportunity to change settings via SMS	Yes Omdurman Son Son Son Son Son Son Son Son Son So
Maximum number of cameras/RS232	El Obolo A N A Share Al Share A Share
Maximum number of cameras/RS485	TRAFRIQUE E DE THE CREE
Maximum number of FLS/RS485	16
Maximum number of FLS/RS232	Kangoni Koninala KENYA
Number of passengers flow registration sensors	Z A I R E Tabora TA N Z A N NE
Internal battery	Yes Wayne Transanytha Pares Salaam
Voice communication	No Labumbashi Lac COMORES
Opportunity to connect KMC-25 Push-to-talk or a compatible one	No Little of Mayatte (ir)
Availability of accelerometer	Yes ZIMBABWE Solais Solais
Availability of gyroscope Walles Band (Rep. of Afr. du Syd)	No out a tappeter op Caborate
Case Equatoriale Sw Swaziland RR Gréco YOUE Yougoslavie	Johannesbyks & Maputo
Intense connector	No Suppose Sup
Intrusion sensor	No
Body material	Plastic
Ingress protection rating	IP54



Weight	150 g
Dimensions	97*68*22 mm
Life time	derinate Mar Note Porto Alexand
Warranty period	1 year Istanbul
Service life	10 years
Internal battery service life	500 charge/discharge cycles, three years maximum
Operating temperature range	-40+ 85 C
Power supply	B Y E Assiont
Average consumed power	0,48 W
Built-in battery	Li-lon, 600 mA
Power supply voltage N L G E R	9-39 V Omdurmano
Voltage range of DAI	0-33 V El Oveld Rhartouti Asmara Thates
Maximum measured frequency of DAI	4 kHz
Maximum voltage supply for the terminal output	30 V
Maximum current supply for the terminal output	80 mA E Spiebbe Netfeel